

PT06 Voltages

Pin	Name	Min	Typ	Max	Units	Condition	
1	Transformer 1	10.5	13	15.5	VAC		
2	Transformer 2	10.5	13	15.5	VAC		
3	Ground						
4	5V DC Out	4.5	5	5	VDC		
5	Reserved						
6	Ball Switch	4.5	5	5	VDC	Normal	
		0	0	0.5	VDC	Activated	
7	Reserved						
8	Pitch A	17	19	20	VDC	Relay Off	
		0	0.8	1.5	VDC	Relay On	
		0	0.6	1	VDC	Nothing Connected	
9	Feed A	17	19	20	VDC	Relay Off	
		0	0.8	1.5	VDC	Relay On	
		0	0.6	1	VDC	Nothing Connected	
10	Yellow LED	4	6	9	VDC	LED Off	
		0	0.8	1.5	VDC	LED On @ Full Brightness	
		0	0.6	1	VDC	Nothing Connected	
11	Red LED	4	6	9	VDC	LED Off	
		0	0.8	1.5	VDC	LED On @ Full Brightness	
		0	0.6	1	VDC	Nothing Connected	
12	Pitch B	17	19	20	VDC	Relay Off	
		0	0.8	1.5	VDC	Relay On	
		0	0.6	1	VDC	Nothing Connected	
13	Feed B	17	19	20	VDC	Relay Off	
		0	0.8	1.5	VDC	Relay On	
		0	0.6	1	VDC	Nothing Connected	
14	Reserved						
15	Ground						
16	SIO 2 Computer	11	13	14	VDC	Normal	
		5		25	VAC		
			0		VDC	Jumper Removed	
17	Ground						
18	SIO 1 Coin	11	13	14	VDC	Normal	
		5		25	VAC		
19	SIO 2 Power Select	11	13	14	VDC	Normal	
		5		25	VAC		
			0		VDC	Jumper Removed	
20	Led Power	11	13	14	VDC	Normal	
		5		25	VAC		
21	Relay Power	17	19	20	VDC		

